
Lady Bug

Materials:

Hook:	TMC100 10-12
	Kamasan B400 10-12
Thread:	Black 6/0
Head:	Yellow foam
Antennas:	Pheasant tail
Body:	Coffee bean
Legs:	Fine black rubber legs
Plus:	Red acrylic paint
	Black permanent marker
	UV glue






- 1 Tie in the thread at the eye of the hook
- 2 Wind it in close turns to the curvature of the hook and back



4 Flip the foam strip backwards 5 Tie it off

6 Tear off or cut off the excess



3 Tie in the foam strip at the eye of the hook



7 Tie in a pheasant tail fibre on each side of the head as an antenna





8 Wind the thread in close turns to the curvature of the hook and back9 Whipfinish



11 Fix the coffee bean on the hook shank using a few drops of instant glue



13 When the paint is dry, draw the contours of the wing case and apply a few black dots on the wing case using a permanent marker



- 16 Cover the underside of the body with UV glue $% \left({\left| {{{\rm{UV}}} \right|_{\rm{T}}} \right)$
- 17 Lay 3 rubber legs into the glue
- 18 Cure the glue with your UV torch



10 Using a saw blade or a file enlarge the slit of the coffee bean



12 Colour the upper side of the coffee bean with red acrylic paint



- 14 Cover the back of the fly with UV glue.
- 15 Cure the glue with your UV torch



19 Trim the legs to the desired length

